

Device Modeling Report

COMPONENTS: TRANSISTOR
PART NUMBER: TG6063
MANUFACTURER: SANYO





Bee Technologies Inc.

TRANSISTOR MODEL


PSpice model parameter	Model description
IS	Saturation Current
BF	Ideal Maximum Forward Beta
NF	Forward Current Emission Coefficient
VAF	Forward Early Voltage
IKF	Forward Beta Roll-off Knee Current
ISE	Non-ideal Base-Emitter Diode Saturation Current
NE	Non-ideal Base-Emitter Diode Emission Coefficient
BR	Ideal Maximum Reverse Beta
NR	Reverse Emission Coefficient
VAR	Reverse Early Voltage
IKR	Reverse Beta Roll-off Knee Current
ISC	Non-ideal Base-Collector Diode Saturation Current
NC	Non-ideal Base-Collector Diode Emission Coefficient
NK	Forward Beta Roll-off Slope Exponent
RE	Emitter Resistance
RB	Base Resistance
RC	Series Collector Resistance
CJE	Zero-bias Emitter-Base Junction Capacitance
VJE	Emitter-Base Junction Potential
MJE	Emitter-Base Junction Grading Coefficient
CJC	Zero-bias Collector-Base Junction Capacitance
VJC	Collector-base Junction Potential
MJC	Collector-base Junction Grading Coefficient
FC	Coefficient for Onset of Forward-bias Depletion Capacitance
TF	Forward Transit Time
XTF	Coefficient for TF Dependency on Vce
VTF	Voltage for TF Dependency on Vce
ITF	Current for TF Dependency on Ic
PTF	Excess Phase at $f=1/2\pi \cdot TF$
TR	Reverse Transit Time
EG	Activation Energy
XTB	Forward Beta Temperature Coefficient
XTI	Temperature Coefficient for IS

Reverse

Reverse Early Voltage Characteristic





Reverse DC Beta Characteristic (I_e vs. h_{FE})




Forward


Forward Early Voltage Characteristic



C-B Capacitance Characteristics




E-B Capacitance Characteristics




Transistor h_{FE} - I_C Characteristics

Circuit Simulation Result




Evaluation Circuit



Comparison Graph

Circuit Simulation Result




Simulation Result


Ic(A)	hFE		Error(%)
	Measurement	Simulation	
-0.001	29.778	29.738	-0.134
-0.002	31.303	31.856	1.661
-0.005	36.680	36.908	0.622
-0.010	37.784	38.042	0.683
-0.020	38.072	38.266	0.510
-0.050	36.780	36.910	0.353
-0.100	34.542	34.854	0.903

$V_{CE(Sat)}-I_C$ Characteristics

Circuit Simulation Result




Evaluation Circuit



Comparison Graph

Circuit Simulation Result




Simulation Result


IC(A)	VCE(sat)		Error(%)
	Measurement	Simulation	
-0.001	-0.210	-0.209	-0.476
-0.002	-0.195	-0.193	-1.026
-0.005	-0.180	-0.178	-1.111
-0.01	-0.175	-0.173	-1.143
-0.02	-0.185	-0.181	-2.162
-0.05	-0.230	-0.223	-3.043
-0.1	-0.310	-0.299	-3.548

$V_{BE(Sat)}-I_C$ Characteristics

Circuit Simulation Result




Evaluation Circuit



Comparison Graph

Circuit Simulation Result




Simulation Result


IC(A)	VBE(sat)		Error(%)
	Measurement	Simulation	
-0.001	-0.694	-0.694	0.000
-0.002	-0.715	-0.712	-0.420
-0.005	-0.744	-0.738	-0.806
-0.01	-0.770	-0.759	-1.429
-0.02	-0.800	-0.784	-2.000
-0.05	-0.853	-0.825	-3.283
-0.1	-0.903	-0.869	-3.765

Switching Characteristics

Circuit simulation result



Evaluation circuit




Simulation result

	Measurement	Simulation	%Error
$t_{stg} \text{ (ns)}$	45.000	43.631	-3.042
$t_f \text{ (ns)}$	5.500	5.324	-3.200


Switching Characteristic

Reference




Output Characteristics

Circuit Simulation Result



Evaluation Circuit



Output Characteristics

Reference

