

Device Modeling Report

COMPONENTS: BRT
PART NUMBER: RN1316
MANUFACTURER: TOSHIBA




Bee Technologies Inc.


PSpice model parameter	Model description
IS	Saturation Current
BF	Ideal Maximum Forward Beta
NF	Forward Current Emission Coefficient
VAF	Forward Early Voltage
IKF	Forward Beta Roll-off Knee Current
ISE	Non-ideal Base-Emitter Diode Saturation Current
NE	Non-ideal Base-Emitter Diode Emission Coefficient
BR	Ideal Maximum Reverse Beta
NR	Reverse Emission Coefficient
VAR	Reverse Early Voltage
IKR	Reverse Beta Roll-off Knee Current
ISC	Non-ideal Base-Collector Diode Saturation Current
NC	Non-ideal Base-Collector Diode Emission Coefficient
NK	Forward Beta Roll-off Slope Exponent
RE	Emitter Resistance
RB	Base Resistance
RC	Series Collector Resistance
CJE	Zero-bias Emitter-Base Junction Capacitance
VJE	Emitter-Base Junction Potential
MJE	Emitter-Base Junction Grading Coefficient
CJC	Zero-bias Collector-Base Junction Capacitance
VJC	Collector-base Junction Potential
MJC	Collector-base Junction Grading Coefficient
FC	Coefficient for Onset of Forward-bias Depletion Capacitance
TF	Forward Transit Time
XTF	Coefficient for TF Dependency on Vce
VTF	Voltage for TF Dependency on Vce
ITF	Current for TF Dependency on Ic
PTF	Excess Phase at $f=1/2\pi \cdot TF$
TR	Reverse Transit Time
EG	Activation Energy
XTB	Forward Beta Temperature Coefficient
XTI	Temperature Coefficient for IS

Input voltage vs. output current (ON characteristics)

Circuit simulation result




Evaluation circuit



Comparison Graph

Circuit Simulation Result




Simulation Result

Condition @ $V_{ce} = 0.2 \text{ V}$


$I_c(\text{mA})$	$V_{I(ON)} (\text{V})$		Error (%)
	Datasheet	Simulation	
0.3	0.94	0.976	3.8298
0.5	0.98	1.0064	2.6939
1	1	0.9994	-0.0600
2	1.1	1.1119	1.0818
5	1.2	1.2219	1.8250
10	1.4	1.3627	-2.6643

Output current vs. input voltage (OFF characteristics)

Circuit simulation result




Evaluation circuit



Comparison Graph

Circuit Simulation Result




Simulation Result

Condition @ $V_{ce} = 5\text{ V}$


$I_c(\mu\text{A})$	$V_{I(Off)} (\text{V})$		Error (%)
	Datasheet	Simulation	
30	0.84	0.864	2.8571
50	0.86	0.886838	3.1207
100	0.89	0.918203	3.1689
200	0.91	0.951931	4.6078
500	0.96	1.0035	4.5313
1000	1.0	1.0496	4.9600

DC current gain vs. output current

Circuit simulation result




Evaluation circuit



Comparison Graph

Circuit Simulation Result




Simulation Result

Condition @ $V_{ce} = 5\text{ V}$


$I_c(\text{mA})$	h_{FE}		Error (%)
	Datasheet	Simulation	
1	13	12.536	-3.5692
2	23	22.754	-1.0696
5	50	47.583	-4.8340
10	80	77.988	-2.5150
20	110	114.901	4.4555
50	120	123.410	2.8417
100	50	50.552	1.1040

Output voltage VS. output current

Circuit simulation result




Evaluation circuit



Comparison Graph

Circuit Simulation Result



Simulation Result

Condition @ $I_C/I_B = 20$

Ic(mA)	V _{CE} (sat) (mV)		Error (%)
	Datasheet	Simulation	
5	0.067	0.065582	-2.1164
10	0.07	0.072306	3.2943
50	0.17	0.171752	1.0306
80	0.26	0.255243	-1.8296