

Device Modeling Report

COMPONENTS:
DIODE/ SCHOOTKY RECTIFIER / STANDARD
PART NUMBER: FSQ10A04
MANUFACTURER: NIEC




Bee Technologies Inc.


PSpice model parameter	Model description
IS	Saturation Current
N	Emission Coefficient
RS	Series Resistance
IKF	High-injection Knee Current
CJO	Zero-bias Junction Capacitance
M	Junction Grading Coefficient
VJ	Junction Potential
ISR	Recombination Current Saturation Value
BV	Reverse Breakdown Voltage(a positive value)
IBV	Reverse Breakdown Current(a positive value)
TT	Transit Time
EG	Energy-band Gap

Forward Current Characteristic

Circuit Simulation Result




Evaluation Circuit



Comparison Graph

Circuit Simulation Result




Simulation Result


Ifwd(A)	Vfwd(V) Measurement	Vfwd(V) Simulation	%Error
1	0.395	0.388	-1.77
2	0.430	0.425	-1.16
5	0.495	0.495	0.00
10	0.585	0.595	1.71
20	0.770	0.780	1.30
40	1.160	1.190	2.59

Junction Capacitance Characteristic

Circuit Simulation Result




Evaluation Circuit



Comparison Graph

Circuit Simulation Result



Simulation Result

Vrev(V)	Cj(pF) Measurement	Cj(pF) Simulation	%Error
1	1010.000	1034.000	2.38
2	808.000	810.000	0.25
5	535.000	544.000	1.68
10	390.000	394.000	1.03
20	285.000	284.000	-0.35
40	211.000	206.000	-2.37